



- Ambient reference conditions: 1,000 mbar, 25°C, 60% relative humidity
- Standby Power Standby duty, operation under variable load, without Over load;
- 3) Prime Power-Continuous duty operation, under variable load 24/24h
   -10% over load permissible 1 hour/12 hours

#### **Features**

- Strong power, high torque, easy to maintain, easy to start;
- Low noise. low emissions:
- Cabinet made of high quality sheet metal, corrosion-resistant, scratch-resistant;
- Canopy sealing performance, high waterproof, dust-proof, rain, dust and other difficult to access;
- Omni-directional control, easy connection and simple;
- Cranes, fork, pull, drag, easy transportation;
- ≥8-hour fuel tanks;
- Open type with 40°C radiator, Soundproof type with 50°C radiator

### **DIESEL GENERATOR SETS**

R-M Series
Powered by MTU Engines

# R-M1000/S

**50**<sub>Hz</sub>

# **Output Ratings**

Three-Phase, 50Hz, 1500RPM			
Output	Prime Power	Standby Power	
Output	1000kVA / 800kW	1100kVA / 880kW	
24.4	- (11)		


Voltage (V)	Frequency (Hz)	Current(A)	Power Factor
380/220	50	1519	0.8
400/230	50	1443	0.8
415/240	50	1391	0.8

#### **Performance Data**


Engine Brand & Model		MTU & 16V2000G65
Alternator Brand & Model		STAMFORD & S6L1D-E4
Control System		DSE7320 / DSE8610
Circuit Breaker Type (Optional)		3 Pole MCCB
		3 Pole ACB
Fuel Consumption (l/hr)	100% Load	190.8
	75% Load	141.7
	50% Load	96.9
	25% Load	53.5


# **Dimensions and Weights**

Content		Open Sets	Soundproof Sets
	L	4730	6050
Dimensions: (mm)	W	2100	2438
	Н	2540	2585
Weight (kg)		7900	9400











### Engine Brand / Model & MTU / 16V2000G65

No. of Cylinders / Alignment	16 / In V	Gross Engine	Prime	890
Cycle	4 Stroke	Power (kW)	Standby	979
Bore / Stroke	130 mm / 150 mm	Compression Ratio		16 : 1
Induction	TCA	Displacement (L)		31.84
Cooling Method	Water	Governing Type		ECM
Lubricant Oil	15W40-CF4	Net weight (kg)		3310
Lubricant Oil Capacity(L)	110	Coolant Capacity(L)		48

#### Alternator Brand / Model & STAMFORD / S6L1D-E4

Rated Capacity(kVA)	1050	A.V.R. Model	MX341
Rated Power(kW)	840	Voltage Regulation (no load- full load)	± 1.0%
THF(BS EN60034 – 1)	<2%	Underspeed Protection	Standard
Bearing Number	Single	Protection	IP23
Windings	100% Copper	Phase Sequence	A(U), B(V), C(W)
Silicon Steel Core Processing	One Piece Punching	TIF(NEMA MG 1-22)	<50
Insulation Class	Н	Excitation System	Self-excited,
Ilisulation Class	11	Excitation System	
Winding Pitch	2/3	Ambient Temp.	50 °C
Amortisseur Winding	Full	Stator Rated Temp.	125 °C

## **Control System:**



**DSE7320** 

DSE8610

- Monitoring an extensive number of engine parameters, the modules will display warnings, shutdown and engine status information on the back-lit LCD screen, illuminated LEDs, remote PC and via SMS text alerts (with external modem).
- The DSE7320 will also monitor the mains (utility) supply. The modules include USB, RS232 and RS485 ports as well as dedicated DSENet® terminals for system expansion.
- Both modules are compatible with electronic (CAN) and non-electronic (magnetic pick-up/alternator sensing) engines and offer an extensive number of flexible inputs, outputs and extensive engine protections so the system can be easily adapted to meet the most demanding industry requirements.
- The extensive list of features includes enhanced event and performance monitoring.
- The DSE8610 is an easy to use multi-generator loadshare system, designed to synchronise up to 32 generators including electronic and non-electronic engines.
- The DSE8610 monitors the generator and indicates operational status and fault conditions, automatically starting or stopping the engine on load demand or fault condition.
- System alarms are annunciated on the LCD screen (multiple language options available), illuminated LED and audible sounder.
- The event log will record 250 events to facilitate easy maintenance. An
  extensive number of fixed and flexible monitoring, metering and protection
  features are included as well as comprehensive communication and system
  expansion options.



#### The Reliable Supplier for Power System Solution

#### **Documents**

Engine parts man	ual and original data	•	Generator set maintenance record manual
Alternator original	data	•	Generator set instruction manual
Controller system	original data	•	Generator combination certificate
Generator set fac	tory test report		

# **Optional**

Engine	Controller System
Water heater	Compartment operation remote control system
Fuel heater	With three remote control screen
Oil heater	Auto Transfer Switch
Secondary silencer	Multiple units are automatically connected in synchronize
Water separator	Centralized monitoring
Alternator	Others
Anti condensation heater	Separate fuel Tank
Permanent magnet generator (PMG)	Buried storage tank
Drop CT( Paralleling)	Fully automatic oil supply system
Other alternator temperature rise level	Remote water tank
Stator winding temperature sensor RTD	Waterproof Type genset
Bearing temperature sensor RTD	Trailer Type genset
Air filter	Soundproof Type genset
	Open Type genset

### **Service Commitment**

- The products provided are all new products. each gensets undergoes strict factory inspection.
- Products are provided with "three guarantees" service, the period is 12 months after the unit is adjusted and the accumulated running time is 1000 hours, whichever comes first.
- The services and accessories of products can be obtained from the after-sales service department (86-510-83781999-1009).





E-Mail: info@rcgpower.com

We reserve the right to make changes in model, technical specification, color, configuration and accessories without prior notice. Please contact the us before ordering.

